

WHAT IS CLAIMED IS:

1. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality of IDTs which are successively arranged on a piezoelectric substrate along a propagation direction of a surface acoustic wave,

wherein:

said first longitudinally connected resonator type surface acoustic wave filter has a transmission phase that is substantially opposite to a transmission phase of said second longitudinally connected resonator type surface acoustic wave filter;

first terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters defining balanced terminals by being connected via a ground or connected in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

sub
A1

0001701-06001
100000-1016000

the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between said first and second longitudinally connected resonator type surface acoustic wave filters.

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality of IDTs successively arranged on a piezoelectric substrate along a propagation direction of a surface acoustic wave, wherein:

first terminals of said first and second

longitudinally connected resonator type surface acoustic wave filters each arranged to define unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters are arranged to define balanced terminals by being connected via a ground or by being connected in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

wherein in said first and second longitudinally connected resonator type surface acoustic wave filters, each of said plurality of IDTs includes a narrow-pitch electrode finger portion, and the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than that of other electrode finger portions of the IDT; and

the pitch of the electrode fingers in said narrow-pitch electrode finger portion is different between said first and second longitudinally connected resonator type surface acoustic wave filters.

3. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality

Cont
as

0984704-06604
T09880 T09880

of IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

Cont
A1
said first longitudinally connected resonator type surface acoustic wave filter has a transmission phase that is substantially opposite to a transmission phase of said second longitudinally connected resonator type surface acoustic wave filter;

first terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each being arranged to define unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each being arranged to define balanced terminals by being connected via a ground or by being connected in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

wherein in said first and second longitudinally connected resonator type surface acoustic wave filters, each of said plurality of IDTs including a narrow-pitch electrode finger portion, and the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than that of other electrode finger portions of the

09891701-063004
T09390 T02T6650

IDT; and

the intercentral distance of two adjacent electrode fingers is different between said first and second longitudinally connected resonator type surface acoustic wave filters, at at least at one location.

4. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality of IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

said first longitudinally connected resonator type surface acoustic wave filter has a transmission phase that is substantially opposite to a transmission phase of said second longitudinally connected resonator type surface acoustic wave filter;

first terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each is arranged to define unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining balanced terminals by being connected via a ground or by

Cont
A¹

000001001000001

being connected in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

wherein in said first and second longitudinally connected resonator type surface acoustic wave filters, each of said plurality of IDTs including a narrow-pitch electrode finger portion, and the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than that of other electrode finger portions of the IDT; and

at least one of the intercentral distance of the two adjacent electrode fingers between adjacent IDTs and the intercentral distance of the two adjacent electrode fingers between the narrow-pitch electrode finger portion and the remaining electrode finger portion, is different between said first and second longitudinally connected resonator type surface acoustic wave filters.

5. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality of IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

Cont
A1

09894701-06001

Cont
A1
said first longitudinally connected resonator type surface acoustic wave filter has a transmission phase that is substantially opposite to a transmission phase of said second longitudinally connected resonator type surface acoustic wave filter;

first terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining balanced terminals by being connected via a ground or in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

wherein in said first and second longitudinally connected resonator type surface acoustic wave filters, each of said plurality of IDTs including a narrow-pitch electrode finger portion, and the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than that of other electrode finger portions of the IDT; and

said longitudinally connected resonator type surface acoustic wave filter further including at least two of the following features (a) to (d):

000001-000001

(a) the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between said first and second longitudinally connected resonator type surface acoustic wave filters;

(b) the pitch of the electrode fingers in said narrow-pitch electrode finger portion is different between said first and second longitudinally connected resonator type surface acoustic wave filters;

(c) the intercentral distance of two adjacent electrode fingers is different between said first and second longitudinally connected resonator type surface acoustic wave filters, at at least at one location; and

(d) at least one of the intercentral distance of the two adjacent electrode fingers between adjacent IDTs and the intercentral distance of the two adjacent electrode fingers between a narrow-pitch electrode finger portion and the remaining electrode finger portion, is different between said first and second longitudinally connected resonator type surface acoustic wave filters.

6. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first and second longitudinally connected resonator type surface acoustic wave filters each having a plurality of IDTs successively arranged on a piezoelectric substrate

Cont
A1

09891701-062604

along the propagation direction of a surface acoustic wave, wherein:

said first longitudinally connected resonator type surface acoustic wave filter has a transmission phase that is substantially opposite to a transmission phase of said second longitudinally connected resonator type surface acoustic wave filter;

first terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining unbalanced terminals by being connected in parallel with each other, and second terminals of said first and second longitudinally connected resonator type surface acoustic wave filters each defining balanced terminals by being connected via a ground or by being connected in series with each other, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of said first and second longitudinally connected resonator type surface acoustic wave filters has, in each of the plural IDTs thereof, a chirp type electrode finger portion, wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is linearly changed along the propagation direction of a surface acoustic wave; and

the configuration of said chirp type electrode finger

Cont
A1

09891701-062601

portion is different between said first and second longitudinally connected resonator type surface acoustic wave filters.

7. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the phase of the second IDT, an unbalanced terminal extending from the second IDT, a balanced terminal extending from each of the first and third IDTs, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is made narrower than that of other electrode finger portions of the IDT; and

the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between a portion where the first and second IDTs are adjacent to each other, and a portion where the second and third IDTs are adjacent to each other.

Cont
A1

09291701-062601

8. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the phase of the second IDT, an unbalanced terminal extending from the second IDT, and a balanced terminal extending from each of the first and third IDTs, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is made narrower than that of other electrode finger portions of the IDT; and

the pitch of the electrode fingers in said narrow-pitch electrode finger portion is different between a portion where the first and second IDTs are adjacent to each other, and a portion where the second and third IDTs are adjacent to each other.

9. A longitudinally connected resonator type surface acoustic wave filter, comprising:

Cont
A1

09091701-062601
109907-007600

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the phase of the second IDT, an unbalanced terminal extending from the second IDT, and a balanced terminal extending from each of the first and third IDTs, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is made narrower than that of other electrode finger portions of the IDT; and

denoting a middle point of said second IDT as a center, the distance between two adjacent electrode fingers is different between opposite sides of said center, at least at one location.

10. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the

Cont
A2

[illegible]

phase of the second IDT, an unbalanced terminal extending from the second IDT, and a balanced terminal extending from each of the first and third IDTs, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is made narrower than that of other electrode finger portions of the IDT; and

the intercentral distance of two adjacent electrode fingers between adjacent IDTs, and/or the intercentral distance of two adjacent electrode fingers between a narrow-pitch electrode finger portion and the electrode finger portion other than the narrow-pitch electrode finger portion, are different between the opposite sides of the second IDT.

11. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the phase of the second IDT, an unbalanced terminal extending from the second IDT, and a balanced terminal extending from

Cont
A1

000001701-000001

[illegible]

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is made narrower than that of other electrode finger portions of the IDT; and

(a) the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between the portion where the first and second IDTs are adjacent to each other, and the portion where the second and third IDTs are adjacent to each other;

(c) denoting the middle point of said second IDT as a center, the distance between two adjacent electrode fingers is different between opposite sides of said center, at least at one location; and

(d) the intercentral distance of two adjacent electrode fingers between adjacent IDTs, and/or the intercentral distance of two adjacent electrode fingers between the narrow-pitch electrode finger portion and the electrode finger portion other than the narrow-pitch electrode finger portion, are different between the opposite sides of the second IDT.

12. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the first and third IDTs have an opposite phase to the phase of the second IDT, an unbalanced terminal extending from the second IDT, and a balanced terminal extending from each of the first and third IDTs, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of said IDTs includes a chirp type electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is linearly changed along the propagation direction of a surface acoustic wave; and

the configuration of said chirp type electrode finger

Cont
A1

09991701-066601

portion is different between a portion where the first and second IDTs are adjacent to each other, and a portion where the second and third IDTs are adjacent to each other.

13. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which has been divided into two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than the pitch of the other electrode finger portion of the IDT; and

the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between a portion where the first and second IDTs are adjacent to each other,

Cont
A1

09991701-062604

and a portion where the second and third IDTs are adjacent to each other.

14. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which is divided into the two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than the pitch of the other electrode finger portion of the IDT; and

the pitch of the electrode fingers in said narrow-pitch electrode finger portion is different between a portion where the first and second IDTs are adjacent to each other, and a portion where the second and third IDTs are

Corr 14
A4

000001704-0500001

adjacent to each other.

15. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which is divided into the two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than the pitch of the other electrode finger portion of the IDT; and

denoting a middle point of said second IDT as a center, the distance between two adjacent electrode fingers is different between opposite sides of said center, at least at one location.

Cont
A1

[illegible]

16. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which is divided into the two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than the pitch of the other electrode finger portion of the IDT; and

the intercentral distance of the two adjacent electrode fingers between adjacent IDTs, and/or the intercentral distance of the two adjacent electrode fingers between the narrow-pitch electrode finger portion and the electrode finger portion other than the narrow-pitch electrode finger portion, are different between opposite sides of the second IDT.

Cont
A1

09891701-098901

17. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which is divided into the two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of the IDTs includes a narrow-pitch electrode finger portion wherein the pitch of one electrode finger portion from the adjacent IDT-side end of said each IDT is narrower than the pitch of the other electrode finger portion of the IDT; and

said longitudinally connected resonator type surface acoustic wave filter further comprising at least two of the following features (a) to (d):

(a) the duty of the electrode fingers in said narrow-pitch electrode finger portion is different between a portion where the first and second IDTs are adjacent to each

Cont
A1

09881704-062601

other, and a portion where the second and third IDTs are adjacent to each other;

(b) the pitch of the electrode fingers in said narrow-pitch electrode finger portion is different between the portion where the first and second IDTs are adjacent to each other, and the portion where the second and third IDTs are adjacent to each other;

(c) denoting a middle point of said second IDT as a center, the distance between two adjacent electrode fingers is different between opposite sides of said center, at least at one location; and

(d) at least one of the intercentral distance of the two adjacent electrode fingers between adjacent IDTs and the intercentral distance of the two adjacent electrode fingers between the narrow-pitch electrode finger portion and the electrode finger portion other than the narrow-pitch electrode finger portion, is different between the opposite sides of the second IDT.

18. A longitudinally connected resonator type surface acoustic wave filter, comprising:

first, second and third IDTs successively arranged on a piezoelectric substrate along the propagation direction of a surface acoustic wave, wherein:

the second IDT is divided into two portions, the first

Cont
A1

1. 100% of the total
 2. 100% of the total
 3. 100% of the total
 4. 100% of the total
 5. 100% of the total
 6. 100% of the total
 7. 100% of the total
 8. 100% of the total
 9. 100% of the total
 10. 100% of the total
 11. 100% of the total
 12. 100% of the total
 13. 100% of the total
 14. 100% of the total
 15. 100% of the total
 16. 100% of the total
 17. 100% of the total
 18. 100% of the total
 19. 100% of the total
 20. 100% of the total
 21. 100% of the total
 22. 100% of the total
 23. 100% of the total
 24. 100% of the total
 25. 100% of the total
 26. 100% of the total
 27. 100% of the total
 28. 100% of the total
 29. 100% of the total
 30. 100% of the total
 31. 100% of the total
 32. 100% of the total
 33. 100% of the total
 34. 100% of the total
 35. 100% of the total
 36. 100% of the total
 37. 100% of the total
 38. 100% of the total
 39. 100% of the total
 40. 100% of the total
 41. 100% of the total
 42. 100% of the total
 43. 100% of the total
 44. 100% of the total
 45. 100% of the total
 46. 100% of the total
 47. 100% of the total
 48. 100% of the total
 49. 100% of the total
 50. 100% of the total
 51. 100% of the total
 52. 100% of the total
 53. 100% of the total
 54. 100% of the total
 55. 100% of the total
 56. 100% of the total
 57. 100% of the total
 58. 100% of the total
 59. 100% of the total
 60. 100% of the total
 61. 100% of the total
 62. 100% of the total
 63. 100% of the total
 64. 100% of the total
 65. 100% of the total
 66. 100% of the total
 67. 100% of the total
 68. 100% of the total
 69. 100% of the total
 70. 100% of the total
 71. 100% of the total
 72. 100% of the total
 73. 100% of the total
 74. 100% of the total
 75. 100% of the total
 76. 100% of the total
 77. 100% of the total
 78. 100% of the total
 79. 100% of the total
 80. 100% of the total
 81. 100% of the total
 82. 100% of the total
 83. 100% of the total
 84. 100% of the total
 85. 100% of the total
 86. 100% of the total
 87. 100% of the total
 88. 100% of the total
 89. 100% of the total
 90. 100% of the total
 91. 100% of the total
 92. 100% of the total
 93. 100% of the total
 94. 100% of the total
 95. 100% of the total
 96. 100% of the total
 97. 100% of the total
 98. 100% of the total
 99. 100% of the total
 100. 100% of the total

and third IDTs having an opposite phase to the phase of the second IDT, an unbalanced terminal extending from each of the first and third IDTs, and a pair of balanced terminals extending from the second IDT which is divided into the two portions, whereby said longitudinally connected resonator type surface acoustic wave filter has a balanced-unbalanced conversion function;

each of said IDTs includes a chirp type electrode finger portion wherein the pitch of one electrode finger portion from an adjacent IDT-side end of said each IDT is linearly changed along the propagation direction of a surface acoustic wave; and

the configuration of said chirp type electrode finger portion is different between a portion where the first and second IDTs are adjacent to each other, and a portion where the second and third IDTs are adjacent to each other.

19. A communication device including a longitudinally connected resonator type surface acoustic wave filter in accordance with any one of claims 1 through 18.

Concluded
A1

09891701.062604
T09290 T0476860